

## S-LINK-1 (ETHERNET)

PC interface for power & energy measurement. Single-channel, USB & Ethernet output.



#### PRODUCT FAMILY KEY FEATURES

READS BOTH POWER AND ENERGY Thermopiles and pyroelectrics

AVAILABLE WITH 1 OR 2 CHANNELS S-LINK-1 and S-LINK-2 models now available

PC-BASED Connects to your PC with included software

SERIAL COMMANDS Serial commands are available on all versions to let you take full control

**FASTEST DATA TRANSFER RATE** Get all the points transferred directly into your PC at 10 kHz/Channel

USB OR ETHERNET Choose your favourite communications port. The USB version is port-powered

#### **EXTERNAL TRIGGER** Every model comes standard with a 2.4 V to 24 V external trigger

### **SPECIFICATIONS**

CONTROLLER AND GUI SPECIFICATIONS	
Digital display size	Computer screen
Data display	Real time, ratio, line plot, histogram, statistics and 3D histogram
External trigger	3-24 V @ 13 mA, optically isolated
Serial commands via	USB or Ethernet
External power supply	9 VDC 1.66 A
POWER METER SPECIFICATIONS	
Device accuracy	±0.75 % for 10 % to full scale
Statistics	Current value, max, min, average, standard deviation, RMS & PTP stability, time
Response time	Current value, max, min, average, standard deviation, RMS & PTP stability, time
ENERGY METER SPECIFICATIONS	
Digital resolution	Normal Mode: Current scale/4096
Device accuracy	±1 % (<500 Hz) ±2 % (500 Hz - 1.2 KHz) ±3 % (1.2 - 6 KHz) ±6 % (6 - 10 kHz)
Repetition rate <sup>1</sup>	10 kHz
Real-time data transfer <sup>2</sup>	10 kHz/Channel in normal mode, no missing point
Statistics	Current value, max, min, average, standard deviation, RMS & PTP stability, pulse #, repetition rate and average power
<ol> <li>Maximum repetition rate may vary with PC and detector speeds.</li> <li>Actual rate may depend on the computer</li> </ol>	
PHYSICAL CHARACTERISTICS	
Dimensions	106W x 34H x 147D mm
Weight	0.424 kg
ORDERING INFORMATION	

Specifications are subject to change without notice. Refer to the user manual for complete specifications.

# INTERESTED IN THIS PRODUCT?



Find your local sales representative at gentec-eo.com/contact-us