## **AC134 Series**

Low Frequency Accelerometer, Side Exit 2 Pin Connector, 500 mV/g, ±10%








## **Product Features**

Designed for low speed Rotors, Main Bearings, and Gear Box Inputs, but can also be used for High Frequency Detection.


Can be used with any application that requires low and high frequency measurements.


- ▶ 500 mV/g Sensitivity, ±10% Sensitivity
- 0.1 Hz for Low Frequency Measurements
  8,000 Hz for High Frequency Detection
- Standard 2 Pin MIL Connection or Integral Cable


Note: Integral Cable Options are only for Permanent Monitoring Applications



Stock Product







,	_\		
Specifications	Standard		Metric
Part Number	AC134		M/AC134
Sensitivity (±10%)		500 mV/g	
Frequency Response (±3dB)	6-480,000 CPM		0,1-8000 Hz
Frequency Response (±10%)	36-180,000 CPM		0,6-3000 Hz
Dynamic Range		± 16 g, peak *Vsource ≥ 22V, 12Vbias	
Electrical			
Settling Time		<2 seconds	
Voltage Source (IEPE)		18-30 VDC	
Constant Current Excitation		2-10 mA	
Spectral Noise @ 10 Hz		1.7 μg/√Hz	
Spectral Noise @ 100 Hz		0.2 μg/√Hz	
Spectral Noise @ 1000 Hz		0.12 μg/√Hz	
Output Impedance		<100 ohm	
Bias Output Voltage		10-14 VDC	
Case Isolation		>10 <sup>8</sup> ohm	

L	Built To Order	Built To Order		
2	Specifications	Standard		Metric
4	<u>Environmental</u>			
0	Operating Temperature Rang	-58 to ge 250°F		-50 to 121°C
0	Maximum Shock Protection		5,000 g, peak	
	Electromagnetic Sensitivity		CE	
	Sealing		Welded, Hermetic	
	Submersible Depth	200 ft.		60 m
	SIL Rating Physical		SIL 2	
	Sensing Element		PZT Ceramic	
	Sensing Structure		Shear Mode	
	Weight	5.7 oz		160 grams
	Case Material		316L Stainless Steel	
	Connector (Non-Integral)		2 Pin MIL- C-5015	
	Danamant Francisco	1,080,000		10000 11-