



# gentec-e

### QE195LP-H-MB-QED-D0

Pyroelectric detector for laser energy measurement up to 700 J.



#### PRODUCT FAMILY KEY FEATURES

CUSTOM-BUILT Contact us with your requirements for a version tailored to your needs

MODULAR CONCEPT Increase the power capability of your detector: 2 different cooling modules

EXTRA LARGE APERTURE Effective aperture of 195 mm Ø

**QED ATTENUATOR AVAILABLE** Measure up to 5X higher energies. Available with optional calibration, all wavelengths between 532 & 1064 nm, or single wavelength. Read more.

TEST TARGET INCLUDED With the MB models

SMART INTERFACE Containing all the calibration data

COMPATIBLE STAND

STAND-D-443

# **SPECIFICATIONS**

#### MEASUREMENT CAPABILITIES

Spectral range <sup>1</sup>	0.3 - 2.1 µm
Repeatability	<0.5%
Maximum repetition frequency <sup>2</sup>	200 Hz
Maximum measurable energy <sup>3</sup>	700 J
Noise equivalent energy <sup>4</sup>	200 µJ
Maximum pulse width <sup>5</sup>	5 ms
Energy calibration uncertainty	±3 %

1. For the calibrated spectral range, see the user manual.

2. These products are custom-built. Contact us with your requirements for a version tailored to your needs.

These products are custom-built. Contact us with your requirements for a version tailored to your needs.
Nominal value. Actual value depends on electrical noise in the measurement system.

5. These products are custom-built. Contact us with your requirements for a version tailored to your needs.

#### DAMAGE THRESHOLDS

Maximum average power density <sup>1</sup>	600 W/cm <sup>2</sup>
Maximum energy density <sup>2</sup>	8 J/cm²
Maximum power	350 W

1. May vary with wavelength and average power.

2. At 1064 nm, 7 ns, 10 Hz. May vary with wavelength and pulse width.

### PHYSICAL CHARACTERISTICS

Cooling	Convection (heatsink)
Aperture diameter	185 mm
Absorber	QED
Dimensions	229H x 229W x 107D mm
Weight	5.3 kg

### ORDERING INFORMATION

QE195LP-H-MB-QED-D0

QE195LP-H-MB-QED-INT-D0





QE195LP-H-MB-QED-INE-D0 QE195LP-H-MB-QED-IDR-D0

Specifications are subject to change without notice. Refer to the user manual for complete specifications.

## INTERESTED IN THIS PRODUCT?

GET A QUOTE

Find your local sales representative at gentec-eo.com/contact-us