



1.2.3 High Energy Pyroelectric Sensors

100µJ to 10J

Features

- Premium DIFH & DIFH2 energy sensors BF coating for highest damage threshold
- Metallic coating for high repetition rates up to 10kHz
- Measure lasers with pulse widths up to 20ms
- Flavors focusing on UV and others focusing on VIS-IR

PE50-DIFH2-C PE50BF-DIFH2-C, PE50-UV-DIFH-C PE50BF-UV-DIFH-C



Model	PE50-DIFH2-C					PE50BF-DIFH2-C					PE50-UV-DIFH-C					PE50BF-UV-DIFH-C					
Use	High repetition lasers requiring high damage threshold					Pulsed lasers requiring very high damage threshold					High repetition lasers requiring high damage threshold					Pulsed lasers requiring very high damage threshold					
Aperture mm	Ø35					Ø35					Ø35					Ø35					
Absorber Type	Metallio	c with di	ffuser			BF with diffuser					Metallic with UV diffuser					BF with UV diffuser					
Spectral Range µm (a)	0.355 – 2.2, 2.94					0.355 – 2.2, 2.94					0.193 - 0.355					0.193 - 0.355					
Surface Reflectivity % approx.	35					35					25					25					
Calibration Uncertainty ±% (a)	3					3					3					3					
Max Pulse Width Setting (d)	2us	30µs	500µs	1ms	5ms	1ms	2ms	5ms	10ms	20ms	2µs	30µs	500µs	1ms	5ms	1ms	2ms	5ms	10ms	20ms	
Energy Scales	_	10J to 2mJ			10J to 20mJ	10J to 2mJ	10J to 2mJ	10J to	10J to	10J to 20mJ	10J to 2mJ			10J to 2mJ	10J to 20mJ	10J to 2mJ	10J to 2mJ	10J to 20mJ		10J to 20mJ	
Lowest Measurable Energy mJ (c)	0.1	0.1	0.1	0.1	0.1	0.2	0.4	0.8	0.8	0.8	0.1	0.1	0.1	0.1	0.1	0.2	0.4	0.8	0.8	0.8	
Max Pulse Width ms		0.03	0.5	1	5	1	2	5	10	20	0.002	0.03	0.5	1	5	1	2	5	10	20	
Maximum Pulse Rate pps	10kHz	5kHz	900Hz	450Hz	100Hz	250Hz	100Hz	50Hz	40Hz	20Hz	10kHz	5kHz	900Hz	450Hz	100Hz	250Hz	100Hz	50Hz	40Hz	20Hz	
Noise on Lowest Range μJ	10	10	10	10	20	40	80	200	200	200	10	10	10	10	20	40	80	200	200	200	
Additional Error with Frequency %	±1.5%	±1.5%		±1% to 450Hz	±1% to 100Hz	±1% to 100Hz ±2.5% to 150Hz ±4.5% to 250Hz	±1%	±1%	±2%	±2%	±1.5%	±1.5%		±1% to 450Hz	±1% to 100Hz	±1% to 100Hz ±2.5% to 150Hz ±4.5% to 250Hz	±1%	±1%	±2%	±2%	
Linearity with Energy for >10% of full scale (for Metallic) and >7% of full scale (for BF) (c)	±1.5%					±2%					±1.5%					±2%					
Maximum Energy Density	J/cm² ®																				
<100ns (7ns)	3					8					2					3					
1µs	15					17					8					8					
300µs	75					75					35					35					
2ms	200					200					95					95					
Maximum Average Power W	25, 40 with optional heat sink (P/N 7Z08267)					25, 40 with optional heat sink (P/N 7Z08267)					25, 40 with optional heat sink (P/N 7Z08267)					25, 40 with optional heat sink (P/N 7Z08267)					
Maximum Average Power Density W/cm ²	200					200					200					200					
Uniformity over surface	±2.5%	over ce	ntral 20n	nm		±2.5% over central 20mm					±2.5% over central 20mm					±2.5% over central 20mm					
Weight kg	0.25					0.25					0.25					0.25					
Compliance	CE, UK	(CA, Chi	ina RoH	S		CE, UKCA, China RoHS					CE, UKCA, China RoHS					CE, UKCA, China RoHS					
Version																					
Part Number	7Z02958					7 Z 02959					7 Z 02960					7Z02961					
Note: (a) Calibration curve is verified and adjusted at specified wavelengths.	Specified wavelengths: 355nm, 532nm, 1064nm, 2100nm and 2940nm.					Specified wavelengths: 355nm, 532nm, 1064nm, 2100nm and 2940nm.					Specified wavelengths: 193nm, 248-266nm and 355nm.					Specified wavelengths: 193nm, 248-266nm and 355nm.					
At other wavelengths, there may Max additional error at other wavelengths not be an additional error up to the specified above: $\pm 2\%$. value given.							Max additional error at other wavelengths not specified above: $\pm 2\%.$					Max additional error at 193nm ±4%. Max additional error at other wavelengths not specified above: ±2% 193nm reading may need 1min irradiation to stabilize.					Max additional error at 193nm ±4%. Max additional error at other wavelengths not specified above: ±2%.				

In order to avoid measurement degradation extra care must be taken to protect sensor from contaminants.

In order to avoid measurement degradation extra care must be taken to protect sensor from contaminants.

Note: (b)

For wavelengths >2.2µm, derate to 10% of above values.
For wavelengths below 500nm, derate to 40% of given values.
For beam size ≤5mm. For 10mm beam, derate to 60% of above values.
For beam size ≤5mm. For 10mm beam, derate to 60% of above values.
For beam size ≤5mm. For 10mm beam, derate to 60% of above values.
For beam size ≤5mm. For 10mm beam, derate to 60% of above values.
Note: (c) With the "user threshold" setting set to minimum. For other settings, the spec is for >10%/57% of full scale or greater than twice the "user threshold", whichever is greater. The user threshold is not available with LaserSfar, Nova/Onfon, Pulsar, USBI and Quasar. For these meters, the threshold is set to minimum and the linearity spec is >10% of full scale. The PE-C series will only operate with Nova or Orion meters with an additional false triggering in noisy environments.
For further information, see the FAQs on our Website.

Note: (c) With the LaserStar, Pulsar, USBI, Quasar and Nova/Orion with adapter only 2 out of 5 pulse wirth settings are available.

For wavelengths <300nm, derate to 50% of given values.
For wavelengths <300nm, derate to 50% of given values.
For wavelengths <300nm, derate to 50% of piven values.
For wavelengths <300nm, derate to 50% of given values.
For wavelengths <300nm, derate to 50% of piven values.
For wavelengths <300nm, derate to 50% of piven values.
For wavelengths <300nm, derate to 60% of above.
For wavelengths <300nm, d

Note: (d) With the LaserStar, Pulsar, USBI, Quasar and Nova/Orion with adapter only 2 out of 5 pulse width settings are available. For PE50BF-DIFH2-C & PE50BF-UV-DIFH-C sensors the 1ms and 10ms settings and for PE50-DIFH2-C & PE50-UV-DIFH-C sensors the 2µs (displayed as "30µs") and 1ms settings. Furthermore, with the diffuser mounted, the sensor may saturate at lower than the maximum energy in some cases. Therefore it is recommended to use these sensors with the newer meters/PC interfaces.

^{*} For drawings please see page 133















